



## Cordless Lamp Charging Rack NWCR-36B

### Description

## Cordless Lamp Charging Rack NWCR-36B High-Efficiency Multi-Lamp Charger

The NWCR-36/B is a double-sided charger rack with 36 charging ports, 18 per side. Each lamp charges independently with an LED per charge port to indicate charging or being fully charged.

### Fast Charging Technology for Wisdom Lamps

Using advanced **intelligent fast charging**, the NWCR-36B reduces charging time significantly:

- **Wisdom Lamp 3D** charges in just **3 hours**
- **Wisdom Lamp 3A** charges in about **5 hours**

This makes it a valuable asset for teams needing fully charged equipment between shifts.

### Higher efficiency, less heat –

Compared with the past generations of the chargers, the charger PCB of NWCR-12B is improved to be more efficient. Even when charged at full power, it generates only a little heat.

### Wide range voltage –

The voltage range of the AC power supply is: 100~240V

The wide range makes the charger applicable to the specific voltage standard in all countries.

### Environmentally-friendly –

The charging rack is designed per the Restriction of Hazardous Substances Directive (RoHS). RoHS standard is strictly followed in the whole process, from choosing the material to designing the production technique.

### Compatibility & Use Cases

This charging rack is compatible with:

- **WISE LITE2 (4.8V)**
- [WISDOM Lamp 3 / 4 \(4.8V\)](#)
- [WISDOM Lamp 6 \(6.8V\)](#)

Perfect for mining operations, search and rescue teams, construction crews, and more.

### Technical specifications

Features	NWCR-36B Specifications
AC input	100~240 V $\pm$ 10%, 8.1 A, 50~60 Hz
DC output voltage	4.80 V/6.8V
DC output current	2000 mA
Size	93.1 × 30 × 106 cm; 36.7 x 11.8 x 41.7 in
Weight	62 kg; 136.69 lb
Model	WISE LITE2(4.8V),WISDOM LAMP3/4(4.8V),WISDOM LAMP6(6.8V)

If you need a Rack with small number of port Check the Cordless Lamp [Charging Rack NWCR-24B](#)